Unit 2,
Delta Court,
Doncaster,
DN9 3GN
text_phone 03333 444 943
sales@theledstore.co | https://theledstore.co/

LED Dimmer Switch - Wall Mount 4 Zone T2112/24V DC RF Remote battery operated, 15A Receiver and Base Plate

£41.88







PRODUCT INFORMATION	
Warranty	1 Year Warranty
Part L Compliant	No
Dimensions	Remote - 139mm x 36mm x 11mm Receiver - 107mm x 75mm x 24.5mm
Weight	0.16kg
TECHNICAL SPECIFICATIONS	
Input Voltage	12/24V DC
Operating Temperature	-30°C to 55°C
Ingress Protection	IP21
Output Voltage	12/24V DC - 1 Channel / 15Amp Max
AVAILABLE OPTIONS	
3-Hour Emergency Version	No
1-10V Dimmable	No
DALI Dimmable	No

The Wall Mount Battery Operated 12/24V DC RF LED Dimming Remote comes with an option of 1, 2, 3 or 4 15Amp receivers for up to 4 zones.

Also come with a base plate so the wall mount dimming remote that can be wall mounted or fixed to a 85mm single back box.

This product is ideal for dimming 12/24V DC LED constant voltage systems such as LED flexible strip.

The remote has range of up to 30m from the receiver.

PLEASE NOTE - The remote requires 2 x AAA battery which is not included as standard - select from the add on options

The max load for the receiver is:

180W @ 12V

360W @ 24V

Additional receivers can be purchased separately here - up to a max of 4 with each controller

DOWNLOAD LED WALL DIMMER RF REMOTE PRODUCT INSTALLATION MANUAL / GUIDE

Unit 2,
Delta Court,
Doncaster,
DN9 3GN
text_phone 03333 444 943
sales@theledstore.co | https://theledstore.co/

DOWNLOAD LED RF RECEIVER PRODUCT INSTALLATION MANUAL / GUIDE