


LED Emergency Exit Sign Light (X10 PACK TRADE BULK) - Blade 3 Hour Maintained/Non-Maintained 3.5W Running Man Fire Exit Sign - Surface Wall or Ceiling Mount with Adjustable Legend

£347.40 £292.80




Blade LED Emergency Exit Sign

Maintained or Non-Maintained operation
Selectable Self Test / Manual Test




WALL OR CEILING MOUNT AS STANDARD



Blade LED Emergency Exit Sign

Maintained and Non-maintained mode
Manual test and Self-test function, complies with ESCD54 standard
LiFePO4 Battery as standard



This 3W LED Emergency Fire Exit Sign Light is a reliable, energy-efficient illuminated running man exit sign, ideal for commercial, retail, office, warehouse, hospitality, school and public building applications. Designed to clearly identify fire exits and escape routes, the box-style LED exit sign is typically installed above doorways, corridors, stairwells and emergency exit routes.

The standard stock model is designed for flexible installation and can be used as either a wall mounted or ceiling mounted emergency exit sign. The exit sign blade can be rotated from the main body of the unit, allowing the same fitting to be adapted on site to suit the required mounting position and escape route layout.

For easy installation, the unit features a removable base plate that is screwed directly to the wall or ceiling first. Once the base plate is securely fixed in position, the main luminaire body simply clips into place, helping make installation faster, cleaner and more convenient.

Supplied complete with interchangeable green running man legends, including Up, Down, Left, Right and Blank options, this LED emergency fire exit sign can be configured to suit different directional requirements. The legends can be installed on either side of the unit, making it suitable for a wide range of installation layouts.

With a 25 metre viewing distance and 6000K daylight white LED output, this illuminated exit sign provides clear visibility in both normal and emergency lighting conditions. The adjustable angle design also allows flexible positioning for improved visibility across corridors, doorways and escape routes.

The fitting supports both maintained and non-maintained emergency operation, with a 3 hour emergency backup duration in the event of a power failure. It is manual and self-test switchable, helping reduce ongoing maintenance and making routine emergency lighting checks easier.

Fitted with a long-life LiFePO4 lithium battery, this LED emergency exit sign offers reliable long-term performance, low maintenance operation and improved battery durability compared with traditional emergency lighting batteries.

Further installation accessories are available separately to support a flexible 6-in-1 installation setup. Depending on the required application and accessories used, the emergency exit sign can be installed as wall mounted, ceiling mounted, suspended hanging, recessed, track mounted or flag mounted, making it suitable for a wide range of commercial and emergency lighting layouts.

Key Features:

- High Power 3.5W LED emergency fire exit sign light - visible from 25m
- Illuminated running man exit sign for emergency escape routes
- Suitable for wall mounted or ceiling mounted installation
- Rotating blade design allows the standard stock model to suit either wall or ceiling mounting
- Easy installation with removable screw-fixed base plate
- Luminaire body clips securely into position after the base plate is installed to the wall or ceiling
- Slimline design means can to next to wall / above doors with ease & minimal disruption
- Outlet cable entry hole at top of base - can go directly into ceiling / wall + quick fix push connector blocks
- Maintained and non-maintained emergency operation
- 3 hour emergency backup duration
- Switch to choose between Manual Key Switch Test OR automatic self-test switchable (key switch or automatic periodic self test with status indicator lights to reduce maintenance)
- Long-life LiFePO4 lithium battery for low maintenance, ongoing use
- 6000K daylight white LED output
- 25 metre viewing distance
- Adjustable angle for improved visibility
- Supplied with Up, Down, Left, Right and Blank legends
- Green running man legends can be installed on either side of the unit
- Box-style emergency exit sign, typically installed above doorways
- Suitable for corridors, stairwells, offices, shops, warehouses, schools, hotels and commercial buildings
- Optional accessories available separately for 6-in-1 installation
- Accessory-supported installation options include wall mount, ceiling mount, hanging, recessed, track mount and flag mount
- Includes routine test record sheet for period maintenance, testing & record keeping in accordance with BS 5266-1 and BS EN 50172

Specification

Product Wattage	3.5W
Product Lumen	110Lm
Lumen/W	31
Emergency Wattage	0.4W
Emergency Lumen	50Lm
Kelvin	6500K
Beam Angle	90°
CRI	80
Lifetime	50,000 hours
Power Factor	0.5
Inrush Current at Start Up	Max. 2A
Product Voltage	220-240V
Hertz	50/60Hz
Battery Spec	LiFePO4 3.2V 600mAh x 1pc
Emergency Duration	3 hours / 180 minutes



Specification

Product Weight 0.75kg
Class Class 2

Unit 2,
Delta Court,
Doncaster,
DN9 3GN
text_phone 03333 444 943
sales@theledstore.co | <https://theledstore.co/>